




# Pre-set Torque Wrench

## Pre-set Torque Wrench Selector Guide

Image	Tooling Category	Milling Cutter Family	Milling Cutter Type	Applicable Pre-set Torque Wrench	
	Milling	MFH	MFH with 10mm Inserts	<b>PST-IP15</b>	IP15 Bit Size • Set at 3.5 Nm (30.9 In-lbs)
			MFH with 14mm Inserts	<b>PST-IP20</b>	IP20 Bit Size • Set at 4.5 Nm (39.8 In-lbs)
			MFH-Mini	<b>PST-IP8</b>	IP8 Bit Size • Set at 1.2 Nm (10.6 In-lbs)
		MEW	MEW with 10mm Inserts	<b>PST-IP8</b>	IP8 Bit Size • Set at 1.2 Nm (10.6 In-lbs)
			MEW with 15mm Inserts	<b>PST-IP15</b>	IP15 Bit Size • Set at 3.5 Nm (30.9 In-lbs)
		MRX	MRX with 8mm Inserts	<b>PST-IP9</b>	IP9 Bit Size • Set at 1.4 Nm (12.4 In-lbs)
			MRX with 10mm Inserts	<b>PST-IP10</b>	IP10 Bit Size • Set at 2.0 Nm (17.7 In-lbs)
			MRX with 12mm Inserts	<b>PST-IP15</b>	IP15 Bit Size • Set at 3.5 Nm (30.9 In-lbs)
			MRX with 16mm Inserts	<b>PST-IP20</b>	IP20 Bit Size • Set at 4.5 Nm (39.8 In-lbs)
		MRW	MRW with 12mm Inserts	<b>PST-IP15</b>	IP15 Bit Size • Set at 3.5 Nm (30.9 In-lbs)
			MRW with 16mm Inserts	<b>PST-IP20</b>	IP20 Bit Size • Set at 4.5 Nm (39.8 In-lbs)
		MFK	All Types	<b>PST-T15</b>	T15 Bit Size • Set at 3.5 Nm (30.9 In-lbs)
		MEC	MEC with 11mm Inserts	<b>PST-T8</b>	T8 Bit Size • Set at 1.2 Nm (10.6 In-lbs)
			MEC with 17mm Inserts	<b>PST-T15</b>	T15 Bit Size • Set at 3.5 Nm (30.9 In-lbs)
		MECH	MECH with 11mm Inserts	<b>PST-T8</b>	T8 Bit Size • Set at 1.2 Nm (10.6 In-lbs)
			MECH with 17mm Inserts	<b>PST-T15</b>	T15 Bit Size • Set at 3.5 Nm (30.9 In-lbs)
		CM	CM with XPMT09 Inserts	<b>PST-T7</b>	T7 Bit Size • Set at 0.8 Nm (7.1 In-lbs)
			CM with XPMT15 Inserts	<b>PST-T10</b>	T10 Bit Size • Set at 2.0 Nm (17.7 In-lbs)
			CM with APET Inserts	<b>PST-T15</b>	T15 Bit Size • Set at 3.5 Nm (30.9 In-lbs)
		EM	EM with XPMT09 Inserts	<b>PST-T7</b>	T7 Bit Size • Set at 0.8 Nm (7.1 In-lbs)
			EM with XPMT15 Inserts	<b>PST-T10</b>	T10 Bit Size • Set at 2.0 Nm (17.7 In-lbs)
		FM	FM	<b>PST-T10</b>	T10 Bit Size • Set at 2.0 Nm (17.7 In-lbs)
			FM-AL	<b>PST-T15</b>	T15 Bit Size • Set at 3.5 Nm (30.9 In-lbs)
		Drilling	DRZ	DRZ...-05G	<b>PST-T6</b>
	DRZ...-06G			<b>PST-T7</b>	T7 Bit Size • Set at 0.8 Nm (7.1 In-lbs)
	DRZ...-08G			<b>PST-T8</b>	T8 Bit Size • Set at 1.2 Nm (10.6 In-lbs)
	DRZ...-10G			<b>PST-T15</b>	T15 Bit Size • Set at 3.5 Nm (30.9 In-lbs)
	DRZ...-12G			<b>PST-T20</b>	T20 Bit Size • Set at 4.5 Nm (39.8 In-lbs)
	DRZ...-15G			<b>PST-T20</b>	T20 Bit Size • Set at 4.5 Nm (39.8 In-lbs)
	DRX		DRX...-04	<b>PST-T6</b>	T6 Bit Size • Set at 0.5 Nm (4.4 In-lbs)
			DRX...-05	<b>PST-T6</b>	T6 Bit Size • Set at 0.5 Nm (4.4 In-lbs)
			DRX...-06	<b>PST-T7</b>	T7 Bit Size • Set at 0.8 Nm (7.1 In-lbs)
			DRX...-07	<b>PST-T8</b>	T8 Bit Size • Set at 1.2 Nm (10.6 In-lbs)
			DRX...-09	<b>PST-T10</b>	T10 Bit Size • Set at 2.0 Nm (17.7 In-lbs)
			DRX...-11	<b>PST-T15</b>	T15 Bit Size • Set at 3.5 Nm (30.9 In-lbs)
			DRX...-14	<b>PST-T20</b>	T20 Bit Size • Set at 4.5 Nm (39.8 In-lbs)
DR			DR with WCMX 04 Insert	<b>PST-T7</b>	T7 Bit Size • Set at 0.8 Nm (7.1 In-lbs)
	DR with WCMX 05 Insert		<b>PST-T9</b>	T9 Bit Size • Set at 1.4 Nm (12.4 In-lbs)	
	DR with WCMX 06 Insert		<b>PST-T10</b>	T10 Bit Size • Set at 2.0 Nm (17.7 In-lbs)	
CD	CD with WCMX 05 Insert		<b>PST-T9</b>	T9 Bit Size • Set at 1.4 Nm (12.4 In-lbs)	
	CD with WCMX 06 Insert		<b>PST-T10</b>	T10 Bit Size • Set at 2.0 Nm (17.7 In-lbs)	
SDR	SDR with TCMT12 Insert		<b>PST-T6</b>	T6 Bit Size • Set at 0.5 Nm (4.4 In-lbs)	
	SDR with TCMT18 Insert		<b>PST-T7</b>	T7 Bit Size • Set at 0.8 Nm (7.1 In-lbs)	
API Ring Groover	API Ring Groover		API with DCMT32 Inserts	<b>PST-T15</b>	T15 Bit Size • Set at 3.5 Nm (30.9 In-lbs)
			API with VCMT22 Inserts	<b>PST-T7</b>	T7 Bit Size • Set at 0.8 Nm (7.1 In-lbs)
			API with VCMT33 Inserts	<b>PST-T15</b>	T15 Bit Size • Set at 3.5 Nm (30.9 In-lbs)

P  
SPARE PARTS